

## Product data sheet

### Characteristics

# GGBL6022CS

Lisse - universal dimmer - 2 gangs - 2 way - 250W/VA



### Main

|                           |  |
|---------------------------|--|
| Range                     | Lisse  |
| Product or component type | Dimmer   |
| Device presentation       | Complete product                                     |
| Load type                 | Incandescent lamp : 250 W<br>230 V AC halogen lamp : |
| Colour tint               | Matt white   |
| Quantity per set          | Set of 1   |

### Complementary

|                                |                                  |
|--------------------------------|----------------------------------|
| Device mounting                | Wall mounted                     |
| Dimmer application             | Inductive load<br>Resistive load |
| [Ue] rated operational voltage | 230 V AC 50 Hz                   |
| Number of gangs                | 2 gangs                          |
| Connections - terminals        | Screw terminals                  |
| Fixing mode                    | By screws : M3.5 25 mm           |
| Material                       | Urea (carbamide) :               |
| Type of packing                | Bag                              |
| Height                         | 43.6 mm                          |
| Width                          | 87 mm                            |
| Depth                          | 87 mm                            |
| Product weight                 | 0.097 kg                         |

### Environment

|                         |                 |
|-------------------------|-----------------|
| Standards               | BS EN 60669-2-1 |
| IP degree of protection | IP20            |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.